

ARAXE



Number of ways:	3
Woofers:	21cm Polypropylen diaphragm, phase plug, 115mm magnet, 39mm coil
Midrange:	17cm Polypropylen diaphragm, 95mm magnet, 25mm coil
Tweeter:	17mm horn tweeter aluminium dome
Crossover: Woofer:	-6dB at 500 Hz
Crossover midrange:	Wide range
Crossover Tweeter:	-12 dB at 4kHz
Sensitivity:	92 dB /2.83V / 1 m
Amplifier requirement:	10 W - 100 W per channel
Impedance:	4 ohms
Bandwidth (3dB):	54Hz—22kHz
Harmonic distortion:	0.5% (90dB)
	0.9% (95dB)
	1.2% (100dB)
Dimensions: HxWxD cm (inches):	900x210x210 - 300 (360x84x84 - 120)
Weight:	18,5kg (41lb)